



Starter Motor Wiring Kit Installation Instructions Part Number: WKS1

Thank you for purchasing our starter motor wiring kit.

Step 1. Disconnect the battery from the vehicle. Always do this step as you don't want to be working with your electrical system while the battery is connected. Never skip this step.

Step 2. Locate the keyed ignition switch in the kit and mount on the dash.

Step 3. Locate the Red wire with the large ring terminal. This ring terminal attaches to the large stud on the starter motor solenoid.

Step 4. Locate the Brown wire with the small ring terminal. This ring terminal attaches to the small stud on the starter motor solenoid.

Step 5. Route both the Red and Brown wires through the firewall to the key switch you installed in Step 2, securing with the cable ties.

Step 6. Locate the #10 ring terminals in the kit. Use these to terminate the Red and Brown wires at the back of the keyed ignition switch.

Step 7. Connect the Red wire to the BAT post on the keyed ignition switch.

Step 8. Connect the Brown wire to the ST post on the keyed ignition switch.

Step 9. Reconnect your battery

Always be safe and disconnect your battery when working on your electrical system!!